



Job Name:

Job Type:

Comments:

Quantity:

93263-98: 1838w H-Force Transformer, 240v, Secondary 12-22v



Width: 21 5/8"

Extends: 1/2"

Height: 1"

Wire: 72" (color/Black)

Material List:

1 Construction - Stainless Steel - Brushed Stainless

Safety Listing:

cETL Listed for Wet Locations

Collection: H-Force

The H-FORCE is the most powerful multi-tap transformer in the low voltage lighting industry perfect for large indoor and outdoor lighting projects.

Maximum Wattage: 1838w

Primary Output: 240v

Secondary Output Taps: 12v, 13v, 14v, 15v, 16v, 17v, 18v, 19v, 20v, 21v, 22v

Secondary Fuse & Lug

Isolated single core construction.

Stainless steel (304 gauge) enclosure with lockable hinged door for easy access to primary and secondary wiring compartment.

Two piece drop-in mounting system and horizontal design provide installation and maintenance ease.

Primary and secondary fuse protection with aluminum lug terminals and individually fused commons for each tap.

Hardwire installation. For use with power cord, order 91642 cord kit (sold separately).

Photocell and timer ready with knock-outs for conduit.

Use of other manufacturers' components and power management system materials will void warranty, listing, and present a possible safety hazard. Please use caution when specifying lamps by selecting the proper voltage, base type, and wattage lamp when designing and installing any lighting system.

UPC #:785652173936

Finish: Brushed Stainless (98)

Shipping Information:

Package Type	Product #	Quantity	UPC	Length	Width	Height	Cube	Weight	UPS Ship
--------------	-----------	----------	-----	--------	-------	--------	------	--------	----------

Individual	93263-98	1	785652173936						Yes
------------	----------	---	--------------	--	--	--	--	--	-----