

Job Name:		Item Number:	
Specifier Name:		Sales Agency:	
Specifier Contact:		Agency Contact:	
Fixture Type:		Comments:	
Quantity:		Approval:	

12V Bulk Pack (16) 1' LED Tape Strips 3000K



L: 192" W: 3/8" H: 1/8"

Description

Ambiance LED Tape provides ultra-low profile LED linear lighting that can be mounted securely in numerous applications with its high-endurance 3M™ adhesive backing. Ambiance LED Tape is dimmable on magnetic and electronic low voltage systems. For magnetic systems, a standard incandescent or magnetic low voltage (MLV) dimmer can be used. For electronic, an electronic low voltage (ELV) dimmer is recommended.

Specifications

Item Number	98608SW-15
Finish	White
Dimensions	L: 192" W: 3/8" H: 1/8"
Voltage	12V
Color Temperature	3000°K
Lumens	2,400
Watts Consumed	48 watts
Efficacy	50.0 lm/w
Color Rendering	>85 CRI
Rated Average Life	50,000 hours to 70%
Safety Listing	cETL Listed for Damp Locations
Warranty	5-Year Limited Warranty

Instruction Sheets

- Trilingual (English, Spanish, and French) (HC-1894FS)

Available Photometry

- LM79 Photometry
- Integrating Sphere Test
- IES File


Shipping Information:

Package Type	Product #	Quantity	UPC	Length	Width	Height	Cube	Weight	UPS Ship
Individual	98608SW-15	1	785652158629	14.25	6	1.58	0.078	1.1	Yes
Master Pack	98608SW-15	5	10785652158626	14.58	8.75	6.25	0.461	6.1	Yes
Shipping Master	98608SW-15	60	20785652158623	39.25	18	18.75	7.666	73.8	Yes

Photometric Diagram:

Zone (Degrees)	Lumens	% of Lamp
0° – 30°	40.8	26.0%
0° – 40°	67.1	42.8%
0° – 60°	119.8	76.5%
0° – 90°	155.8	99.5%
90° – 180°	0.8	0.5%
0° – 180°	156.6	100%

		Horizontal Angle (Degrees)		
		0°	45°	90°
Vertical Angle (Degrees)	0°	18280	18280	18280
	45°	13670	14340	17120
	55°	12390	13020	16220
	65°	10670	11150	14650
	75°	8254	8326	11460
	85°	5027	4321	2737



Photometry based on (1) 98606SW(-xx) 1' length 12V LED Tape section in 3000°K.

Component Diagram:



STEP 1

Choose LED Tape Strips
Select tape length, voltage, color temperature and face color based on your desired specifications.



STEP 2

Select Connectors & Cables
Determine required connectors and cuts to achieve your system configuration.



STEP 3

Select Transformers
Multiply the number of feet in your run by 3 watts to determine transformer size. Match voltage of the transformer to your LED tape's voltage.



Optional Components
Mount tape with included 3M™ industrial adhesive backing or mounting clips.



7400 Linder Ave. | Skokie, Illinois 60077 | 800-347-5483
© 2013 Sea Gull Lighting LLC, a Generation Brands Company.

